



STAGE V
COMPLIANT

EPW SERIES



Portable generators can be used to power tools and provide emergency backup, as well as tackle site jobs and property improvement works; making it ideal for both work and recreational activities.

The **EPW Series** portable generators provide power where and when you need it.

- MANUAL + ELECTRIC START**
- PORTABILITY**
- 13L** **24L** **LONG RUNNING TIME**
- BATTERY CHARGER**
- DIGITAL DISPLAY**
- OIL BOTTLE FUNNEL**



PRODUCT INFO
ALWAYS AVAILABLE ONLINE

Scan the QR to get useful information: product usage and maintenance video tutorials, technical data sheet, direct access to the Service&Parts division and to the usage and maintenance manuals.

- A** Pramac engine for maximum performance on all applications
- B** Automatic Oil guard
- C** Digital display to tracks engine runtime
- D** Fuel gauge to track gasoline levels
- E** Quick starting instruction (QR code and decal)
- F** Schuko sockets and 12V DC
- G** Wheels Kit included



AUTOMATIC VOLTAGE REGULATOR:
HOW DOES IT WORK?

Pramac gensets with Automatic Voltage Regulator (AVR) use an electronic control that stabilizes the voltage values, improving the performance and operation of the connected equipment.



	EPW 3000	EPW 5000	EPW 7000
Single Phase Max Power	2900 Watts	4100 Watts	6500 Watts
Single Phase Rated Power	2700 Watts	4000 Watts	6000 Watts
Voltage / Hz	230 V / 50 Hz	230 V / 50 Hz	230 V / 50 Hz
Running time at 50% load	11.5 Hours	8 Hours	11 Hours
Fuel	Petrol	Petrol	Petrol
Fuel tank capacity	13 L	13 L	24 L
Displacement	212 cc	274 cc	420 cc
Speed (rpm)	3000 rpm	3000 rpm	3000 rpm
Starting System	Recoil + Electric	Recoil + Electric	Recoil + Electric
Guaranteed sound level (LWA)	96	97	103
Noise emission at 7 m	68 dB(A)	69 dB(A)	75 dB(A)
Genset dimension LxWxH (mm)	635 X 595 X 502	635 X 662 X 502	758 X 666 X 618
Dry Weight	49 Kg	61 Kg	86 Kg
Socket type Standard EU	2 x Schuko 230V 16A -12 V DC	2 x Schuko 230V 16A -12 V DC	2 x Schuko 230V 16A -12 V DC 1x CEE 230V 32A
Oil guard	✓	✓	✓
Fuel level gauge	✓	✓	✓
Thermal protection	✓	✓	✓
Hour / Volt / Frequency meter	✓	✓	✓
Wheel kit	✓	✓	✓



YOUTUBE TUTORIAL

www.pramac.com | www.pramacparts.com